

# Atari STacy

## Complete Electrolytic Capacitor Replacement List

### Main PCB

| #       | Type   | Description | DigiKey        |
|---------|--------|-------------|----------------|
| C3      | Radial | 10uf 16v    | 493-11317-1-ND |
| C14,C15 | Radial | 47uf 16v    | 493-5361-1-ND  |
| C17,C29 | Axial  | 100uf 16v   | 493-14397-ND   |
| C31     | Radial | 100uf 16v   | 493-5010-1-ND  |
| C56     | Axial  | 10uf 16v    | 493-14809-ND   |
| C60     | Axial  | 220uf 16v   | TVX1C221MAD-ND |
| C61     | Axial  | 2200uf 16v  | 493-14399-ND   |

### Sub PCB

| #  | Type  | Description | DigiKey      |
|----|-------|-------------|--------------|
| C7 | Axial | 1000uf 16v  | 493-14398-ND |

### DC to DC Board

| #         | Type   | Description         | DigiKey        |
|-----------|--------|---------------------|----------------|
| C101,C113 | Radial | 1000uf 25v          | 493-4897-1-ND  |
| C114      | Radial | 1000uf 16v          | 493-4880-1-ND  |
| C102,C103 | Radial | 1000uf 10v          | 493-11831-1-ND |
| C105      | Radial | 100uf 35v           | 493-11564-1-ND |
| C107      | Radial | 220uf 10v           | 493-11573-1-ND |
| C106,C116 | Radial | 220uf 16v           | 493-11395-1-ND |
| C108      | Radial | 47uf 25v            | 493-1817-ND    |
| C109,C112 | Radial | 10uf 25v            | 493-1810-ND    |
| C117      | Radial | 2200uf 10v          | 493-1751-ND    |
| C110,C119 | Radial | 4.7uf 50v           | 493-1889-ND    |
| C115      | Radial | 330uf 16v           | 493-1784-ND    |
| C118      | Radial | 100uf 10v           | 493-1736-ND    |
| C104      | Radial | 1000uf 6.3v         | 493-11731-1-ND |
| C111      | Radial | 47uf 10v (Bi-Polar) | 493-12677-1-ND |